

Tehnički list za artikl: SR3PDIPS03

PDU PRO Switched, 18xCombo (C13, C15, C19, C21), 24xC13, 400V, 16A

Mjerenje po fazi, (mjerenje po utičnici može se dobiti nadogradnjom licence), uklapanje po utičnici, uklj. montažni nosač s vijcima



SCHRACK-Info

- PDU PRO Switched
- Metering per phase/li>
- Can be upgraded to measuring per socket at any time via licence (SR3PAB0011,SR3PAB0012,SR3PAB0013)
- switchable sockets
- Input: 16 A / 400 V | 11 kW
- Supply cable: 3,0 m | 2,5 mm²
- with CEE plug 16 A red
- Output: 24x C13 IEC Socket + 18x Combo C13/C15/C19/C21
- Integrated function for measuring current, voltage, reactive, apparent and active power, Reactive, apparent and active energy, frequency and power factor
- Hot-swappable controller and power supply unit
- Integrated web server with web interface 1x Gbit/s (PoE) and 1x 10/100Mbit/s Ethernet connection
- Interface for PDU network (up to 20 PDUs)
- 1x RJ45 interface for up to ten external sensors
- 1x USB-C port (USB 2.0)
- 2.4" TFT color display
- Incl. frames for color coding (blue, red)

- Incl. mounting brackets (L-shaped) </l

Tehnički podaci

Neto duljina (mm)	1.678,20
Neto širina (mm)	56,00
Neto visina (mm)	71,00
EAN	4057298230523
CIJENA	3.922,00
Min. temperatura okoline (°C)	0
Maks. temperatura okoline (°C)	50
Nazivni napon	400V
IP stupanj zaštite	IP20
Tip proizvoda	Switched
Broj utičnica	42
Outlet type	24 x IEC320 C13 + 18 x Combo Socket (C13/C15/C19/C21)
Nazivna struja (A)	16
Phases per feed	3
Tip priključka	CEE 16 A red
Protokol	LDAP IPv6 IPv4 DNS SNMPv1 SSH HTTP SNMPv3 SNMPv2 NTP SSH2 DHCP ModBus /TCP SMTP HTTPS SNMP Trap Syslog
Način ugradnje	Bracket (L-shape)

PDU PRO Switched, 18xCombo (C13, C15, C19, C21), 24xC13, 400V, 16A

SR3PDIPS03

Mjerenje po fazi, (mjerenje po utičnici može se dobiti nadogradnjom licence), uklapanje po utičnici, uklj. montažni nosač s vijcima