

Tehnički list za artikl: SR3PDIPS04

PDU PRO Switched, 36xCombo (C13,C15,C19,C21), 400V, 16A, RCM

Mjerenje po fazi, (mjerenje po utičnici može se dobiti nadogradnjom licence), nadzor diferencijalne struje po fazi, uklapanje po utičnici, uklj. montažni nosač s vijcima



SCHRACK-Info

- PDU PRO Switched RCM
- Metering per phase
- Can be upgraded to measuring per socket at any time via licence (SR3PAB0011,SR3PAB0012,SR3PAB0013)
- Residual Current Monitoring per phase, Typ B
- switchable sockets
- Input: 16 A / 400 V | 11 kW
- Supply cable: 3,0 m | 2,5 mm²
- with CEE plug 16 A red
- Output: 36x Combo C13/C15/C19/C21
- Integrated function for measuring current, voltage, reactive, apparent and active power, Reactive, apparent and active energy, frequency and power factor
- Hot-swappable controller and power supply unit
- Integrated web server with web interface 1x Gbit/s (PoE) and 1x 10/100Mbit/s Ethernet connection
- Interface for PDU network (up to 20 PDUs)
- 1x RJ45 interface for up to ten external sensors
- 1x USB-C port (USB 2.0)
- 2.4" TFT color display

- Incl. frames for color coding (blue, red)
- Incl. mounting brackets (L-shaped) </l

Tehnički podaci

Neto duljina (mm)	1.696,50
Neto širina (mm)	56,00
Neto visina (mm)	71,00
EAN	4057298230530
CIJENA	4.122,00
Min. temperatura okoline (°C)	0
Maks. temperatura okoline (°C)	50
Nazivni napon	400V
IP stupanj zaštite	IP20
Tip proizvoda	Switched
Broj utičnica	36
Outlet type	36 x Combo Socket (C13/C15/C19/C21)
Nazivna struja (A)	16
Phases per feed	3
Tip priključka	CEE 16 A red
Protokol	LDAP IPv6 IPv4 DNS SNMPv1 SSH HTTP SNMPv3 SNMPv2 NTP SSH2 DHCP ModBus /TCP SMTP HTTPS SNMP Trap Syslog
Način ugradnje	Bracket (L-shape)

PDU PRO Switched, 36xCombo (C13,C15,C19,C21), 400V, 16A, RCM

Mjerenje po fazi, (mjerenje po utičnici može se dobiti nadogradnjom licence), nadzor diferencijalne struje po fazi, uklapanje po utičnici, uklj. montažni nosač s vijcima

SR3PDIPS04